



Wall Access Control Reader

Reader Type:	MiFare RFID 13.56MHz
Controller:	All in-one
Power Supply:	12VDC 3A
Output Type:	Dry contact relay, 3A max.
Reader Size:	78 x 153 x 22 (mm)
Memory:	Audi trail last 400 events
Lock Relay:	Dry contact or powered output - Field Selectable
Exit Button Input:	Yes, 1 input momentary contact
Tamper Switch:	Yes, 1 output
Door Bell:	Yes, 1 output

